

PROCESS FOR PRODUCING A DOPED SEMICONDUCTOR SUBSTRATE

5 Background of the Invention:

Field of the Invention:

10 The invention relates to a process for producing a doped semiconductor substrate. The present invention relates in particular to a process for producing what are known as "retrograde" or "buried retrograde" doping profiles in semiconductor substrates, as are used, for example, for the fabrication of large-scale integrated CMOS circuits.

15 The continuing miniaturization of integrated circuits, in particular CMOS circuits, requires increasingly small MOS transistors. In this context, in particular the channel length of the MOS transistors is being reduced to an increasing extent. Unfortunately, however, the increasingly small MOS transistors have properties that are no longer
20 correctly described by the conventional transistor models that are directed at transistors with a channel length of more than about 2 μm . Accordingly, these properties are often combined under the heading "short-channel effects". One example of a significant short-channel effect is the influence of the gate
25 size on the threshold voltage (V_T) of the transistor. In

transistors with channel lengths of shorter than $0.7\text{ }\mu\text{m}$, the threshold voltage is generally reduced with an increasingly short channel length (V_T roll-off).

5 To compensate for the short-channel effects, hitherto the doping in the channel between the source and the drain has been increased. Therefore, by way of example, in the case of transistors with a channel length of $0.25\text{ }\mu\text{m}$, doping of approximately 3×10^{17} per cm^2 is used. However, a high channel doping of this nature leads to a reduced mobility of the charge carriers in the channel. Furthermore, high channel doping leads to a relatively high threshold voltage. Both effects of the relatively high channel doping are generally undesirable. Therefore, it has been proposed to bypass these difficulties by using what are known as "retrograde" doping profiles in the channel region. Retrograde doping profiles are characterized by the fact that, starting from the surface of the semiconductor substrate, the doping, at least across a predetermined region, rises with increasing depth. It has
20 been found that doping profiles of this nature are able to successfully compensate for short-channel effects without the mobility of the charge carriers being significantly impaired. What are known as delta doping profiles, in which the doping is restricted to a very small spatial region, are also able to
25 successfully compensate for short-channel effects without the

mobility of the charge carriers being significantly impaired.
In both cases, it is desirable for the maximum doping to be
brought as close as possible to the surface of the
semiconductor substrate while at the same time maintaining low
5 doping at the surface.

Unfortunately, steep, retrofit doping profiles or delta doping
profiles of this nature cannot be produced using the
conventional doping processes employed in mass production.

Therefore, a few alternatives for the production of steep,
retrofit doping profiles have been proposed. U.S. Patent No.
5,963,801 (Aronowitz et al.) describes a process for forming a
retrograde doping profile that is based on a dopant
implantation at energy levels of 150 to 220 keV using the
channeling effect. If the dopant implantation is oriented
along a preferred crystallographic direction of the silicon
crystal, the dopant can penetrate significantly more deeply
into the silicon substrate than would otherwise be possible
with the same level of implantation energy. U.S. Patent No.

5,989,963 (Luning et al.) describes a process for producing a
retrograde doping profile that is based on a dopant
implantation with a subsequent heat treatment in a highly pure
inert gas atmosphere using the transient enhanced diffusion
(TED) effect. However, both processes are relatively

difficult to control and monitor, so that they have not so far
been able to establish themselves in industrial production.

The publication titled "0.1 μm Delta-doped MOSFET Using Post Low-energy Implanting Selective Epitaxy" by K. Noda et al. Symposium on VLSI Technology Digest of Technical Papers 3A.2 (1994) describes a process for producing a delta doping profile by the use of selective silicon epitaxy. However, the process is very complex and therefore unsuitable for industrial application, which is dependent in particular on throughput and reproducibility.

Summary of the Invention:

It is accordingly an object of the invention to provide a process for producing a doped semiconductor substrate which overcomes the above-mentioned disadvantages of the prior art processed of this general type, which can produce steep doping profiles and is suitable for use in mass production.

With the foregoing and other objects in view there is provided, in accordance with the invention, a process for producing a doped semiconductor substrate. The process includes the following steps: providing a semiconductor substrate; producing a doping at a surface of the semiconductor substrate; applying a layer selected from the group consisting of a polycrystalline layer and an amorphous layer to the surface; and carrying out a heat treatment step for producing an epitaxial layer and a buried doping.

10404360 041201
The process according to the invention can be used to produce
a buried, precisely defined doping layer in a monocrystalline
semiconductor substrate. The doping layer lies at a
5 predetermined depth of the semiconductor substrate, the depth
being determined substantially by the thickness of the applied
polycrystalline and/or amorphous layer (poly/ α layer). The
free selection of the thickness of the poly/ α layer and,
independently of this, the free selection of the doping
concentration of the doping layer below allow a considerable
freedom in the formation of the three-dimensional doping
configuration, which is otherwise only possible with complex
process steps such as selective epitaxy or molecular beam
epitaxy (MBE). Although the process according to the
invention has been developed with a view to the fabrication of
MOS transistors in the deep sub- μ m range (gate length <200
nm), the process is not restricted to applications for the
fabrication of doping profiles of NMOS and PMOS transistor
channels, but rather can be used wherever buried doping layers
20 or delta doping are advantageous.

The heat treatment is preferably carried out at a temperature
of approximately 600° to 700° C, particularly preferably 650°
C. The low temperature minimizes the diffusion of the doping
25 layer into the adjoining regions. Consequently, the doping

layer remains highly doped and the diffusion of the doping material into the adjoining regions is minimized. Autodoping, i.e. the doping of a layer with little or no doping as a result of a doping material from the adjoining highly doped layer diffusing into it, can thus be reduced to a minimum. This is particularly advantageous if the poly/ α layer, which is then crystallized in the process according to the invention, is intended to define the region of a transistor channel of high conductivity.

One difficulty when applying a monocrystalline (epitaxial) layer to a monocrystalline semiconductor substrate, in particular to a silicon semiconductor substrate, is the spontaneous formation of a natural oxide layer on the semiconductor substrate. The natural oxide can impede the monocrystalline growth of a further layer and may have an adverse effect on the electrical properties of the semiconductor substrate after the application of the further layer. Unfortunately, the formation of the natural oxide layer can only be prevented with considerable difficulty with the conventional processes for application of poly/ α layers, for example an LPCVD process step. Therefore, according to one embodiment of the present invention, it is preferable if an ion bombardment is carried out prior to the final heat treatment, serving to destroy the natural oxide layer.

According to a further embodiment of the present invention, it is preferable if a rapid thermal annealing (RTA) process step is carried out prior to the final heat treatment. The RTA process step likewise destroys the oxide layer that may form between the poly/ α layer and the substrate. The heating in the RTA process step is preferably so short that the doping profile of the doping layer remains substantially unchanged.

The vertical doping profile of the semiconductor substrate after application of the process according to the invention is composed of the doping profile of the poly/ α layer, the doping profile of the doping layer and the doping profile of the lower layers below. Preferably, the poly/ α layer is not doped during or after the deposition.

The doping on the substrate surface is preferably produced by implantation, in which case it is preferable to use doping materials with a low diffusion constant, such as for example Sb, As or In, so that the doping or doping layer has a sharply defined doping profile. Since the doping of the doping layer takes place prior to the application of the poly/ α layer and can therefore take place from the surface of the doping layer, the doping can also be carried out by all other customary doping methods.

0304360 "07404
The vertical doping profile that results from the processes according to the invention is particularly suitable for the doping of a channel region for large-scale integrated MOS transistors. Both processes allow a low degree of doping at the semiconductor surface, the region in which the transistor channel current subsequently flows (previously the poly/ α layer), and a high level of doping directly below the transistor channel (doping layer). The low level of doping in the channel region ensures a high charge carrier mobility, so that the slope of the transistor characteristic and therefore the switching speed of the transistor are high, while the high level of doping below the channel ensures good suppression of the punch-through between drain and source. The suppression of the punch-through therefore ensures that the MOS transistors remain controllable even with very short channel lengths, in particular channel lengths in the sub- μ m range.

20 The semiconductor substrate is preferably made from monocrystalline silicon. However, it is also possible for other semiconductor materials, such as for example GaAs or germanium, to be used as the semiconductor substrate. The poly/ α layer which is to be applied to the semiconductor substrate may also consist of various semiconductor materials.
25 However, preferred materials are materials with a similar

lattice structure to that of the semiconductor substrate, so that monocrystalline growth of the poly/ α layer that is to be crystallized on the semiconductor substrate is ensured.

Preferably, however, the poly/ α layer is made from silicon, in

5 particular if the semiconductor substrate is also made from silicon. The poly/ α layer is preferably applied to the doped semiconductor substrate using an inexpensive low-pressure chemical vapor deposition (LPCVD) process. The temperature is preferably low during this step, so that the doping atoms of the adjoining doping layer substantially do not diffuse and the poly/ α layer is not contaminated by diffusion of the diffusion materials from the doping layer (autodoping). A further advantage of the low temperature is the smaller grain size of the poly/ α layer, which is predominantly amorphous at below 580° C and facilitates subsequent crystallization. An
15 example of a preferred temperature for the low-pressure CVD process step is 500° C to 600° C.

The thickness of the poly/ α layer can be selected freely in a
20 wide range depending on the particular application. It may lie in the range from a few nanometers up to the micrometer range. For the application of the process according to the invention for the fabrication of an MOS transistor channel, the thickness of the poly/ α layer is preferably about 20 nm to

25 40 nm.

According to a preferred embodiment of the present invention,
an amorphous layer that extends to a predetermined depth into
the semiconductor substrate is produced by ion bombardment
5 before the heat treatment step. The thickness of the
amorphous layer is substantially determined by the energy and
atomic mass of the ions. It is preferable for ions which on
the one hand are sufficiently heavy for amorphization of the
semiconductor substrate and on the other hand are incorporated
10 in the semiconductor lattice during the subsequent
crystallization in such a way that the semiconductor
characteristics of the semiconductor substrate remain
substantially unchanged in electronic terms to be selected for
the bombardment. For a silicon substrate, it is preferable to
15 use germanium ions, since they are heavier than silicon and
can be incorporated in the silicon lattice without problems.
However, it is also possible for the semiconductor substrate
to be bombarded with silicon, noble gas and/or other ions,
provided that they do not substantially change the electronic
20 characteristics after the crystallization.

The amorphous layer preferably extends vertically through the
poly/ α layer, so that on the one hand the poly/ α layer is
completely amorphized, but on the other the hand natural oxide
25 layer which has formed on the principal surface prior to the

coating with the poly/ α layer and is now embedded between the poly/ α layer and semiconductor substrate is destroyed by the ion bombardment. The amorphous layer preferably extends so far into the semiconductor substrate that the boundary layer
5 between amorphous layer and non-amorphized semiconductor substrate is sufficiently far away from the functional structures that are yet to be produced on the semiconductor substrate surface. The reason for this is that experience has shown that the boundary layer between the amorphous layer and the non-amorphized semiconductor substrate has a high level of
10 lattice imperfections and lattice defects (end-of-range defects) after the crystallization, which may lead to high levels of leakage currents, traps or other defects and may therefore impair the functionality of transistors or other structures on the semiconductor substrate.
15

To produce a transistor channel using the process according to the invention, by way of example the layer thickness of the amorphous layer is preferably selected in such a way that it
20 extends through the doping layer, so that the end-of-range defects lie at a lower level than the doping layer in the semiconductor substrate and therefore do not affect the transistor channel. A further advantage of the amorphous layer that extends through the doping layer is that the doping
25 layer can be simultaneously annealed during the

crystallization. The amorphous layer is preferably approximately 500 to 1000 nm thick.

The dose of ion bombardment is preferably to be selected in such a way that the amorphous layer is completely amorphized, in order then to grow again on the semiconductor substrate in monocrystalline form at low temperature. For germanium, a dose of preferably $3 \times 10^{14} \text{ cm}^{-2}$ is used for the amorphization.

After the amorphization, the amorphous layer is crystallized, i.e. is grown again in monocrystalline form on the non-amorphized semiconductor substrate (solid-phase epitaxy).

This process step is preferably carried out by a heat treatment at a preferred temperature of between 600° and 700° C, preferably at 650° C, so that the doping profile of the doping layer is only affected to an insignificant extent. In particular, the low temperature makes it possible to ensure that only very small amounts of doping material diffuse into the region of the previous poly/ α layer, so that this region maintains its high charge carrier mobility. The duration of this temperature step is dependent on the thickness of the amorphous layer that is to be crystallized. For an amorphous layer of about 500 nm, the duration is preferably only a few minutes.

According to a further embodiment of the present invention, a RTA process step which breaks up the natural oxide layer which is embedded between poly/ α layer and doping layer is carried out before the heat treatment step. The RTA process step
5 preferably heats the semiconductor substrate to a temperature of 1000° to 1100° Celsius with a preferred duration of 10 to 60 seconds. As a result of this high-temperature process step, the oxide layer is generally broken down into sub-nm oxide islands (SiO_x sub-nm beads) that, however, do not present any problems for most applications.

Then, a solid-phase epitaxy is once again carried out. In this case, too, a low temperature of around 600° to 700° Celsius is preferred, so that the doping profile does not
15 become blurred as a result of diffusion. However, it is only necessary to crystallize the poly/ α layer, so that the crystallization process duration is shorter than the process with additional ion bombardment for the same layer structure.

20 Other features which are considered as characteristic for the invention are set forth in the appended claims.

Although the invention is illustrated and described herein as embodied in a process for producing a doped semiconductor
25 substrate, it is nevertheless not intended to be limited to

the details shown, since various modifications and structural changes may be made therein without departing from the spirit of the invention and within the scope and range of equivalents of the claims.

5

The construction and method of operation of the invention, however, together with additional objects and advantages thereof will be best understood from the following description of specific embodiments when read in connection with the accompanying drawings.

Brief Description of the Drawings:

Figs. 1a-1d are diagrammatic, partial, sectional views of steps of a first embodiment of a process according to the invention and associated vertical doping profiles; and

Figs. 2a-2b are partial sectional views of a second embodiment of the process according to the invention and the associated vertical doping profiles.

20

Description of the Preferred Embodiments:

In all the figures of the drawing, sub-features and integral parts that correspond to one another bear the same reference symbol in each case. Referring now to the figures of the drawing in detail and first, particularly, to Figs. 1a-1d thereof, there is shown a first embodiment of a process

25

according to the invention. The first embodiment is part of, for example, a sequence of process steps for the fabrication of MOS transistors with a very short gate length. The doping profile that is produced in accordance with the invention ensures, in a region of a transistor channel, that, a punch-through between a drain and a source is suppressed through a high implantation dose and, on the other hand, a good charge carrier mobility in the transistor channel is ensured on account of low doping.

Fig. 1a shows a semiconductor substrate 1 made from monocrystalline silicon with a principal surface 2, at which a doping 3 has been produced, preferably by ion implantation. A vertical doping profile 5 is composed of a doping profile of a semiconductor base substrate 5a, which in the embodiment is flat and is provided, for example, by the basic doping of the wafer or a doping well in which a transistor is to be embedded. A doping profile 5b of the doping layer 3 is provided by the doping process. If the doping is produced by ion implantation, the doping profile 5b of the doping layer 3 is substantially provided by a Gaussian distribution, the precise form of which is influenced by parameters such as implantation energy, atomic mass of the implant and dose.

In the embodiment shown, the doping is carried out preferably with boron ions for the NMOS channel and As or Sb ions for the

PMOS channel, so that a doping profile in delta form is produced. Fig. 1a also shows a very thin natural oxide layer 4, which is formed on the doping layer 3 as a result of oxygen in the environment.

5

Fig. 1b shows the semiconductor substrate 1 after a poly/ α layer 7 of silicon has been deposited on the principal surface 2. The deposition preferably takes place by a standard low-pressure chemical vapor deposition (LPCVD) process using preferably undoped silicon. The deposition is preferably carried out in one step for the PMOS and NMOS channels. The thickness of the poly/ α layer 7 is preferably sufficient to encompass the subsequent transistor channel cross section. It is preferably 20 nm to 40 nm. On account of the absence of a subsequent or in-situ doping step, the doping profile of the poly/ α layer 5c is very low. However, it is also possible to use doped poly/ α layers. Since in this embodiment the poly/ α layer defines the transistor channel region, however, a doping which is as low as possible is desirable, in order to obtain a layer with very good charge carrier mobility after the crystallization.

20

The temperature during the LPCVD process is preferably low, preferably between 500° C - 600° C, so that the doping profile of the doping layer 5b cannot run out and penetrate into the

25

poly/ α layer as a result of high levels of diffusion.

Moreover, a grain size of the poly/ α layer 7 becomes smaller at increasingly low temperatures, which facilitates subsequent flawless crystallization. The natural oxide layer 4 is now

5 embedded between the poly/ α layer 7 and the doping layer 3.

Fig. 1c shows the semiconductor substrate 1 during an ion bombardment 10 for producing an amorphous layer 13 (post-amorphization). Amorphization is preferably carried out using heavy ions, in particular using germanium ions, which are subsequently incorporated in the silicon lattice without significantly changing the electrical properties of the silicon lattice. The thickness of the amorphous layer 13 is indicated by a double arrow 14. The amorphous layer 13 extends vertically through the poly/ α layer 7 and preferably through the doping layer 3 down to a predetermined depth of the semiconductor substrate 1, to a line 15, which represents the amorphous/crystalline transition after the ion bombardment.

20

The amorphous/crystalline transition is important because it is impossible to bring about complete amorphization at the boundary region of the ion bombardment, so that lattice defects (end-of-range defects) remain in that region during

25 the crystallization, which may lead to high levels of leakage

current, traps or the like and may impair the function of the transistor. For this reason, the thickness of the amorphous layer 13 is selected to be sufficiently great for the end-of-range defects to lie outside the region of influence of the subsequent transistor channel region. A preferred thickness of the amorphous layer 13, the arrow 14, in the embodiment is 500 nm to 1000 nm.

In addition to the fact that the end-of-range defects are forced a greater depth into the semiconductor substrate 1, the ion bombardment 10 also destroys the natural oxide layer 4, so that a continuously monocrystalline, epitaxial layer can be produced by the subsequent heat treatment (solid-phase epitaxy).

Fig. 1d shows the semiconductor substrate 1 after the crystallization. The crystallization preferably takes place by a heat treatment at low temperature, preferably at 650° C, in order to ensure that the doping profile of the doping layer does not become blurred as a result of high levels of diffusion. The material of the amorphous layer 13 with the thickness 14 characterized by the double arrow has grown in monocrystalline form onto the non-amorphized semiconductor substrate 12 (solid-phase epitaxy), so that an epitaxial layer 20 has been formed. After this process step, only a thin layer with end-of-range defects 22 remains. The region is the

transition region between what was formerly the non-amorphized semiconductor substrate 12 (Fig. 1c) and the amorphous layer 13, which does not merge flawlessly during the crystallization. Since this region lies outside the doping layer, as seen from the transistor channel, the defects there cannot influence the performance of the transistor.

Fig. 1d also shows that the natural doping layer 4 has disappeared, so that a substantially flawless transition is produced between the doping layer 3 and what was previously the poly/ α layer 7. It can also be seen that the doping profile 5 has not changed or has only changed to an insignificant extent during the process step.

Finally, it is preferable to carry out a wet etching operation, in order to remove oxide residues from the surface of the epitaxial layer 20 and to improve the surface quality for a gate oxide that is then to be applied.

To increase the throughput, the solid-phase epitaxy may also be carried out in one operation at the same time as the production of the gate oxide. It is thus possible to dispense with an additional heat treatment for the solid-phase epitaxy. In this case, the wet etching for removal of oxide residues is carried out before the solid-phase epitaxy.

Figs. 2a and 2b show a second embodiment of the process according to the invention for the same application as in the embodiment described above. The first steps are identical to the steps shown in Figs. 1a and 1b. Now, however, to destroy the natural oxide layer 4, there is no ion bombardment of the semiconductor substrate 1, instead a rapid thermal annealing (RTA) process step is carried out. The high-temperature process step destroys the natural oxide layer 4 to such an extent that only sub-nm SiO_x oxide islands 25 which have no influence whatsoever on the function of the transistor channel remain. The high-temperature process step is preferably carried out using a RTA furnace at a temperature of approximately 1050° C and for 20 seconds.

The high-temperature step is followed by a heat treatment of the semiconductor substrate at low temperatures, as in the first embodiment described above. The temperature is once again about 600° C - 700° C, preferably about 650° C.

However, the duration of the heat treatment may be shorter, since now only the poly/ α layer, with a layer thickness of 20 nm to 40 nm, has to be crystallized and therefore converted into an epitaxial layer. As in the first exemplary embodiment, a wet etching operation is preferably carried out after the heat treatment, in order to eliminate oxide residues on the surface and to improve the quality of the semiconductor substrate surface before the gate oxide is applied.

Next, the gate oxide, the gate electrode and the source and drain regions of the transistors can be produced using conventional methods, which are not explained in further
5 detail here.

The process according to the invention enables a retrograde doping profile or a delta doping to be produced in a relatively simple and inexpensive way. The process according to the invention uses individual process steps that are already used in the mass production of integrated circuits and can accordingly be configured for a high throughput.

10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216